



ACCURATE POWER INDUSTRIAL GENERAL TRADING LLC

VP-250



**VOLVO
PENTA**

STAMFORD

GENERATING SET MODEL WVS 250

Output Ratings	Prime	Standby
400 V, 3 ph, 50 Hz, 1500 rpm	250 kVA	274 kVA
	200 kW	219 kW
480 V, 3 ph, 60 Hz, 1800 rpm	257 kVA	279 kVA
	203 kW	224 kW
Power Factor : 0.8		

STANDARD SPECIFICATIONS

- Volvo four stroke heavy duty high performance industrial type diesel engine
- ENGINE FILTRATION SYSTEM
 - Cartridge type dry air filter
 - Two cartridge type fuel filters
 - Full flow lube oil filter
 All filters have replaceable elements
- COOLING RADIATOR
Radiator and cooling fan, complete with safety guards, designed to cool the engine at high ambient temperatures (consult your dealer for deration factors)

XHAUST SYSTEM
Heavy duty Industrial Exhaust Silencer
Silencer noise reduction level

IRCUIT BREAKER TYPE
ABB 3 pole MCCB. (4 pole is optional)

UEL SYSTEM
On Generating sets upto 700kVA, the baseframe design is incorporated with an integral fuel tank with a capacity of approx. 8 hours running at full load. The tank is supplied complete with fill cap breather, fuel speed and return lines to the engine and drain plug.

7. ALTERNATOR
7.1 INSULATION SYSTEM
• Insulation : Class H
• All windings are impregnated in either a triple dip thermosetting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polyester resin.
• Heavy coat of antitracking varnish additional protection against moisture or condensation.

7.2 AUTOMATIC VOLTAGE REGULATOR (AVR)
The fully sealed AVR maintains the voltage regulation at $\pm 0.5\%$. Nominal adjustment by means of a trim pot incorporated on the AVR.

7.3 MOTOR STARTING
An overload capacity equivalent to 300% of the full load impedance at zero power factor can be sustained for 10 sec., when AREP or PMG option is fitted.

8. MOUNTING ARRANGEMENT
8.1 BASE FRAME
The complete generating set is mounted as a whole on a heavy duty fabricated steel baseframe.

8.2 COUPLING
The engine and alternator are directly coupled by means of an SAE flange. The engine flywheel is flexibly coupled to the alternator rotor.

8.3 ANTI-VIBRATION MOUNTING PADS
Anti-vibration pads are affixed between the engine / alternator feet and the baseframe thus ensuring complete vibration isolation of the rotating assembly.

ENGINE / TECHNICAL DATA

Engine Make	Volvo Penta
Engine Model	TAD734GE
Governing Type	Electronic
Number of Cylinders	6
Cylinder Arrangement	Vertical In Line
Bore and Stroke mm	108x130
Displacement / Cubic Capacity ltrs	7.15
Aspiration	Turbocharged
Cycle	4 stroke
Combustion System	Direct Injection
Compression Ratio	17:1

Address: City avenue Business Building Opposite Pullman Residency
Next to Deira city Centre Port Saeed , Deira Dubai UAE

+971 4 294 0033 +971 56 300 0982 +971 50 727 6909



www.accuratepower-group.com



Frequency and Engine Speed	50Hz & 1500rpm			60Hz & 1800rpm
	Prime			Prime
Gross Engine Power kWm	219			223
Fuel Consumption @50%load l/hr	30.09			31.31
@75%load l/hr	42.043			44
@100%load l/hr	52.7			54.78
Oil Consumption (l/hr)	0.03			0.03
Oil Sump Capacity, l	24			24
Heat Rejection at Exhaust (Standby) kW	177			189
Exhaust Temperature °C Standby	550			510
Radiator Cooling Air Flow : m ³ /s	5.2			6.5
Combustion Air Flow (Standby) : m ³ /min	16.3			18.9
Exhaust Gas Flow (Standby) : m ³ /min	33.4			37.9
Dimension (mm) & Weight (Kg)	Length	Width	Height	Weight
Open	2862	1071	1818	2650
Soundproof	3995	1410	2270	3300

STANDARD SPECIFICATIONS

8.4 SAFETY GUARDS

The fan and fan drive along with the battery charging alternator are safety guard protected for personnel protection.

9. FACTORY TESTS

- The generating set is load tested before dispatch.
- All protective devices control functions and site load conditions are simulated. The generator and its systems are checked before dispatch.

10. EQUIPMENT FINISHING

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability.

11. DOCUMENTATIONS

Operation and Maintenance manual, circuit wiring diagrams and commissioning/fault finding instruction leaflets are accompanied with the generator.

CONTROL PANEL

Make Deep Sea
Model DSE4510

The DSE4510 is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.

Metering and Alarm Indications:

- Generator Frequency
- Underspeed, Overspeed
- Generator volts(L-L, L-N)
- Generator Current
- Engine Oil Pressure
- Engine Coolant Temperature
- Fuel Level
- Hours Run Counter
- Battery Volts
- Fail to start/stop
- Emergency Stop
- Failed to reach loading voltage/frequency
- Charge fail
- Loss of magnetic pick-up signal-Optional
- Low DC Voltage
- CAN diagnostics and CAN fail/error

ALTERNATOR DATA

Make	Stamford
Model	UCDI274K
No. of bearings	1
Insulation Class	H
Total Harmonic Content	On load 3.5%
Wires	6 / 12
Ingress Protection	IP23
Excitation System	Shunt / Self Excited
Winding Pitch	2/3(n°6)
AVR Model	R150 / SX460
Overspeed	2250 mn ⁻¹
Voltage Regulation	±1%
Short Circuit Capacity	-
AREP & PMG Excitation System Available as optional	